

# ACCESSORIES FOR ROBERTSHAW THERMOSTATS



**9020i**  
**9025i**

### Remote Indoor (9020i) and Outdoor (9025i) Sensors (use with i-series only)

The sensors are designed to sense air temperature at a remote location and send this information to the thermostat.

- Installs with simple twisted pair wiring
- Automatic configuration with i-series thermostats
- Up to 300 ft. range
- Temperature range of -40°F to 158 °F (outdoor sensor only)

## Backplates

### Backplates

Provides a clean finish to cover unwanted marks from previously installed thermostats. Styled to blend in with each thermostat model.

#### Model Series

- 9010-1 Standard – 9400 series, 9500 series, 9550 series 9600 series  
 9011-1 i-series – 9700i series, 9800i series, 9850i series, 9900i series  
 9012-1 Designer – 8400 series, 8600 series  
 10-531 300 series



**190**  
**series**

### Thermostat Guard Kits

- Protects thermostat from tampering
- Secured lock system
- Non-yellowing UV resistant plastic or 18/22 gauge steel with baked enamel finish
- Available with two mounting base types: solid or ring

## Plastic Thermostat Guard Kits

Part Number	Cover Shape	Cover Dimensions (inside)	Cover Material		
			Transparent	Opaque	
190-050	Square	Solid - 5-1/4" (L) X 4-5/8" (W) X 3-1/4" (D)	•		
190-051		Ring - 5-1/4" (L) X 4-5/8" (W) X 3-1/4" (D)		•	
190-052	Rectangle	Solid - 6-1/4" (L) X 3-1/2" (W) X 3-1/4" (D)	•		
190-053		Ring - 6-3/8" (L) X 3-1/2" (W) X 3-1/4" (D)		•	
190-054	Square	Solid - 3-7/8" (L) X 3-1/2" (W) X 2-1/2" (D)	•		
190-055				•	
190-068	Rectangle	Solid - 8-1/4" (L) X 5" (W) X 3-1/2" (D)	•		
190-069		Ring - 7-1/8" (L) X 4-5/8" (W) X 3-5/8" (D)		•	
190-056	Rectangle	Solid - 4-1/4" (L) X 7-5/8" (W) X 2-1/8" (D)	•		
190-057		Ring - 4-1/8" (L) X 7-1/16" (W) X 2-1/4" (D)		•	
190-072	Rectangle	Solid - 8-1/4" (L) X 5-3/8" (W) X 3-1/2" (D)	Transparent Bronze		
		Ring - 8-1/8" (L) X 4-5/8" (W) X 3-5/8" (D)			
190-073	Rectangle	Solid - 6-3/8" (L) X 3-1/2" (W) X 3" (D)			
		Ring - 6-3/8" (L) X 3-1/2" (W) X 1/4" (D)			

## Metal Thermostat Guard Kits

Part Number	Cover Shape	Cover Dimensions (inside)	Base Type	
			Solid	Ring
190-060	Square	3-7/8" (L) X 3-1/2" (W) X 2-1/2" (D)	•	
190-061	Rectangle	6-13/8" (L) X 3-1/2" (W) X 3" (D)	•	
190-062		6-3/8" (L) X 3-1/2" (W) X 3-1/4" (D)		•
190-063	Square	5-1/4" (L) X 4-5/8" (W) X 3" (D)	•	
190-064		5-1/4" (L) X 4-5/8" (W) X 3" (D)		•
190-065	Rectangle	6-1/4" (L) X 4-3/4" (W) X 3" (D)	•	
190-067		6" (L) X 3-11/16" (W) X 3-1/8" (D)		•
190-070		7-1/4" (L) X 5-3/8" (W) X 3-1/2" (D)	•	
190-071		6-3/8" (L) X 4-1/2" (W) X 3-9/16" (D)		•
190-074		9-3/8" (L) X 6-3/4" (W) X 3" (D)		•

**invensys**<sup>®</sup>

**Controls Americas**

515 South Promenade Avenue  
Corona California 92879-1736 USA  
Telephone +1 800 951 5526 Facsimile +1 630 260 7299  
iccacustomerservice@invensys.com  
Technical Service Telephone +1 800 445 8299  
Technical Service Facsimile +1 630 260 7243  
technicalservice@invensys.com

**Controls Americas**

3505 Laird Road Unit #14  
Mississauga Ontario L5L 5Y7 Canada  
Customer Service Telephone +1 800 387 7978  
Customer Service Facsimile +1 905 828 1265  
iccacustomerservice@invensys.com

[www.icca.invensys.com](http://www.icca.invensys.com)

©2005 Invensys Controls Americas 11/05 - #150-1410K